

# CBCS SCHEME



USN

--	--	--	--	--	--	--	--	--	--

15EC52

Fifth Semester B.E. Degree Examination, June/July 2019

## Digital Signal Processing

Time: 3 hrs.

Max. Marks: 80

Note: Answer any FIVE full questions, choosing ONE full question from each module.

### Module-1

- Describe the process of frequency domain sampling and reconstruction of discrete time signals. (10 Marks)
  - Using linearity property find the DFT of the sequence  $x(n) = \cos\left(\frac{\pi n}{4}\right) + \sin\left(\frac{\pi}{2}n\right)$  consider  $N=4$ . (06 Marks)

OR

- State and prove the i) circular time shift ii) circular time reversal properties of DFT. (08 Marks)
  - Solve by concentric circle or graphical method to find circular convolution  $x(n) = \{1, 3, 5, 3\}$  and  $h(n) = \{2, 3, 1, 1\}$ . (04 Marks)
  - Derive the expression for the relationship of DFT with Z – transforms. (04 Marks)

### Module-2

- State and prove the following properties :
    - Circular correlation
    - Parseval's theorem. (06 marks)
  - Consider a FIR filter with impulse response  $h(n) = \{3, 2, 1, 1\}$ . If the input is  $x(n) = \{1, 2, 3, 3, 2, 1, -1, -2, -3, 5, 6, -1, 2, 0, 2, 1\}$ . Find the output use overlap – same method. Assuming the length of block is 9. (10 Marks)

OR

- Explain the linear filtering of long data sequences using overlap-add method. (08 marks)
  - An FIR filter has the impulse response of  $h(n) = \left\{\frac{1}{2}, 2, 3\right\}$ . Determine the response of the filter to the input sequence  $x(n) = \left\{\frac{1}{2}, 2\right\}$  use DFT and IDFT and verify the result using direct computation of linear convolution. (08 Marks)

### Module-3

- Develop DIT–FFT algorithm and obtain the signal flow diagram for  $N = 8$ . (08 Marks)
  - Determine the IDFT of  $X(K) = \{4, 1 - j2.414, 0, 1 - j0.414, 0, 1 + j0.414, 0, 1 + j2.414\}$  using inverse – radix 2 DIT – FFT algorithm. (08 Marks)

OR

- Define chirp Z–transform. What are the applications of chirp–Z transform. (04 Marks)
  - The DFT of the following sequence using DIF – FFT algorithm  $x_1(n) = \{1, 1, 1, 0, 0, 1, 1, 1\}$  (ii) using the results in (i) Find DFT of signal  $x_2(n) = \{1, 1, 1, 1, 1, 0, 0, 1\}$  consider  $N = 8$ . (12 Marks)

1 of 2

Important Note : 1. On completing your answers, compulsorily draw diagonal cross lines on the remaining blank pages.  
2. Any revealing of identification, appeal to evaluator and /or equations written eg, 42+8 = 50, will be treated as malpractice.

**Module-4**

- 7 a. Obtain the direct form I, direct form II, cascade and parallel form realization for the following system.  $y(n) = 0.75y(n-1) - 0.125y(n-2) + 6x(n) + 7x(n-1) + x(n-2)$ . (08 Marks)
- b. Realize the system given by the difference equation :  
 $y(n) = -0.1y(n-1) + 0.72y(n-2) + 0.7x(n) - 0.252x(n-2)$   
 Use parallel form. Is this system stable? Determine its impulse response. (08 Marks)

**OR**

- 8 a. Design an IIR digital filter that when used in the prefilter A/D – H(z) – D/A structure will SATISFY the following equivalent along specifications. (10 Marks)
- LPF with  $-1\text{dB}$  cutoff at  $100\pi$  rad/sec
  - stopband attenuation of  $35\text{dB}$  or greater at  $1000\pi$  rad/sec.
  - monotonic stop band and pass band
  - sampling rate of  $2000$  samples/sec.
- b. Obtain H(z) using impulse invariance method for the following analog filter  $5\text{Hz}$  sampling frequency  $H_a(S) = \frac{2}{(S+1)(s+2)}$ . (06 Marks)

**Module-5**

- 9 a. Realize a linear phase FIR filter with the following impulse response.  
 $h(n) = \sigma(n) + \frac{1}{4}\sigma(n-1) - \frac{1}{8}\sigma(n-2) + \frac{1}{4}\sigma(n-3) + \sigma(n-4)$ . (06 Marks)
- b. Consider a 3-stage FIR lattice structure having the coefficients  $K_1 = 0.65$ ,  $K_2 = -0.34$ ,  $K_3 = 0.8$ . Evaluate its impulse response by tracing a unit impulse  $\sigma(n)$  at its input through the Lattice structure. Also, draw its direct form-1 structure. (10 Marks)

**OR**

- 10 a. the desired frequency response of a LPF

$$H_d(w) = \begin{cases} e^{-j3w} & |w| < 3\pi/4 \\ 0 & 3\pi/4 < |w| < \pi \end{cases}$$

Find the impulse response  $h(n)$  using Hamming window. Determine the frequency response of FIR filter. Consider  $N = 7$ . (10 Marks)

- b. Explain the following terms :

- Hamming window
- Hanning window
- Bartlet window.

(06 Marks)

\*\*\*\*\*