

10EE55

Fifth Semester B.E. Degree Examination, Dec.2019/Jan.2020 Modern Control Theory

Time: 3 hrs.

Max. Marks:100

Note: Answer any FIVE full questions, selecting atleast TWO questions from each part.

PART - A


- a. What are the advantages of Modern Control Theory over Conventional Control theory?
 (04 Marks)
 - b. Obtain the two state models of the Transfer function given by

$$\frac{Y(s)}{U(s)} = \frac{2S^2 + 3S + 4}{S^3 + 3S^2 + 4S + 5}.$$

(06 Marks)


c. Obtain the state model of the Electrical Network shown in fig. Q1(c).

(10 Marks)



2 a. For the mechanical system shown in fig. Q2(a), obtain the state model.

(06 Marks)



and Y₂ are outputs

Fig.Q2(a)

b. Obtain the Jordan Canonical state model of the system.


$$T(s) = \frac{Y(s)}{U(s)} = \frac{S^2 + 2S + 4}{(S+2)^3 (S+3)}$$

(08 Marks)

= 4 FEB 20201

c. Obtain the state model of the plant of the system shown in fig. Q2(c).

(06 Marks)



3 a. Find Transfer matrix for MIMO system having state model.

$$\overset{\circ}{\mathbf{x}} = \begin{bmatrix} 2 & -1 & 0 \\ 1 & 1 & 2 \\ -1 & 0 & 1 \end{bmatrix} \mathbf{x} + \begin{bmatrix} -1 & 0 \\ 1 & 0 \\ 0 & 2 \end{bmatrix} \mathbf{u} \quad ; \quad \mathbf{y} = \begin{bmatrix} 1 & 1 & 0 \\ 1 & 0 & 1 \end{bmatrix} \mathbf{x} . \tag{10 Marks}$$

b. Obtain Eigen values, Eigen vector and Modal matrix for

$$A = \begin{bmatrix} 0 & 1 & 0 \\ 3 & 0 & 2 \\ -12 & -7 & -6 \end{bmatrix}$$
. Also find Diagonal Matrix. (10 Marks)

a. Obtain the solution of the system which is described by

Given $A = \begin{bmatrix} 0 & 2 \\ -1 & -3 \end{bmatrix}$ using Cayley Hamilton theorem. (07 Marks)

c. Check controllability and observability of system given by

Check controllability and observability of system given by
$$\overset{\circ}{\mathbf{x}} = \begin{bmatrix} 1 & 1 \\ -2 & -1 \end{bmatrix} \mathbf{x} + \begin{bmatrix} 0 \\ 1 \end{bmatrix} \mathbf{u}(\mathbf{t}) \qquad \mathbf{y} = \begin{bmatrix} 1 & 0 \end{bmatrix} \mathbf{x}.$$
(06 Marks)

a. Explain the types of Controllers.

(04 Marks)

b. Consider the system described by x = Ax + Bu.

$$A = \begin{bmatrix} 0 & 1 & 0 \\ 0 & 0 & 1 \\ -1 & -5 & -6 \end{bmatrix} \qquad B = \begin{bmatrix} 0 \\ 0 \\ 1 \end{bmatrix}$$

By using the state feedback control u = -Kx, it is desired to have closed loop poles at $S = -1 \pm j 1$, S = -10. Determine feedback gain matrix.

c. An Observable system is described by

$$\hat{\mathbf{x}} = \begin{bmatrix} 1 & 2 & 0 \\ 3 & -1 & 1 \\ 0 & 2 & 0 \end{bmatrix} \mathbf{x} + \begin{bmatrix} 2 \\ 1 \\ 1 \end{bmatrix} \mathbf{u} ; \quad \mathbf{y} = [0 \ 0 \ 1] \mathbf{x}.$$

Design a state observer so that eigen values are at -4, $-3 \pm$ (08 Marks)

a. Explain the properties of Nonlinear systems. 6

(08 Marks)

- b. Explain the following types of nonlinearities:
 - ii) Relay with dead zone iii) Back lash Friction. i) Saturation (12 Marks)
- a. What are types of singular points and explain them?

(06 Marks)

b. Explain Isocline method of finding phase trajecteries.

(06 Marks)

c. Using Delta method, find the phase trajectories of the following system.

$$x + 2x + 4x = 0.$$
 (08 Marks)

a. Explain the following terms with graphical representation:

i) Asymptotic stability ii) Asymptotic stability in the large iii) Instability. (06 Marks)

- b. Find whether following Quadratics form is positive definite or not:
 - i) $V(x) = x_1^2 + 4x_2^2 + x_2^2 + 2x_1x_2 2x_2x_3 4x_1x_3$.

ii)
$$V(x) = -5x_1^2 - 2x_2^2 - x_3^2 - 2x_1x_2 + 2x_2x_3$$
. (04 Marks)

c. A second order, linear, time - invariant system is described by

$$\overset{0}{\mathbf{x}} = \begin{vmatrix} 0 & 1 \\ -1 & -1 \end{vmatrix} \mathbf{x} \cdot$$

Assuming the matrix Q in the equation $A^{T}P + PA = -Q$ to be identity matrix.

i) Solve for the matrix P ii) Obtain the Liapunov function V(x)Investigate stability of the origin of the system. (10 Marks)