


USN

--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

10EC52



**Fifth Semester B.E. Degree Examination, July/August 2021**  
**Digital Signal Processing**

Time: 3 hrs.

Max. Marks: 100

**Note: 1. Answer any FIVE full questions.**  
**2. Use of prototype tables are not permitted.**

- 1 a. Derive the DFT expression from DTFT expression. (05 Marks)
- b. If  $x(n) = 1 \quad 0 \leq n \leq 5$  and  $x(z)$  its z transform. If  $x(z)$  is sampled at  $z = e^{j\frac{2\pi}{4}k} \quad 0 \leq k \leq 3$ .  
 $= 0$  elsewhere  
 Find  $y(n)$  obtained as IDFT of  $x(k)$ . (07 Marks)
- c. Prove the following identities:
  - i)  $W_N^{K+N} = W_N^K$       ii)  $W_N^{K+\frac{N}{2}} = -W_N^K$
  - iii)  $\text{DFT}(\delta(n)) = 1$       iv)  $\text{DFT}[x^*(n)] = X^*(N-K)$  (08 Marks)
- 2 a. State and prove the time convolution property. (06 Marks)
- b. Find the 4 point DFT of  $x(n) = 2.5, 1 - j2, -0.5, 1 + j0.5$  using the matrix method. (06 Marks)
- c. Let  $X_p(n)$  be a periodic sequence with fundamental period  $N$ . Let  $X_1(k)$  denote the  $N$ -point DFT of one period of  $X_p(n)$  and  $X_3(k)$  be the  $3N$  point DFT of three periods of  $X_p(n)$ . What is the relationship between  $X_1(k)$  and  $X_3(k)$ . (08 Marks)
- 3 a. Perform the linear convolution of the following sequences by overlap and add method.  
 $x(n) = 1, -2, 3, 2, -3, 4, 3, -4, \dots$  and  $h(n) = 1, 2, -1$   
 use 5 point circular convolution. Verify by the direct method of linear convolution. (10 Marks)
- b. Calculate the number of complex multiplications and complex additions for  $N = 256$  for both the direct DFT and FFT. (05 Marks)
- c. Draw the basic Butterfly diagram of radix-2 DIT FFT and DIF-FFT. (05 Marks)
- 4 a. Given a sequence  $x(n) = 0, 1, 2, 3, 4, 5, 6, 7$  determine  $X(k)$  using DIT FFT. Show the intermediate values. (10 Marks)
- b. Compute the IDFT of the sequence  $X(k) = 12, 0, 0, 0, 4, 0, 0, 0$  using DIF – FFT. (10 Marks)
- 5 a. Design an analog band pass filter to meet the following specifications:
  - i)  $f_u = 20\text{kHz}$      $f_L = 50\text{Hz}$
  - ii)  $k_p = -3.0103\text{db}$
  - iii) Stop band attenuation of atleast 20db at 20Hz and 45kHz. (12 Marks)
- b. Find the order of the filter and pole locations for a Chebyshev analog low pass filter that has a 3db PB ripple cut-off of 100rad/sec and a stop band attenuation of 25db or greater for all radian frequencies past 250rad/sec. (08 Marks)

CMRIT LIBRARY  
 BANGALORE - 560 037

Important Note : 1. On completing your answers, compulsorily draw diagonal cross lines on the remaining blank pages.  
 2. Any revealing of identification, appeal to evaluator and /or equations written eg, 42+8 = 50, will be treated as malpractice.

- 6 a. An LTI system is described by the equation  $y(n] + 2y(n-1) - y(n-2) = x(n)$  determine the cascade and parallel realization. (12 Marks)
- b. Determine the lattice co-efficients corresponding to the FIR system with system function  $H(z) = 1 + \frac{7}{9}z^{-1} + \frac{3}{5}z^{-2}$  and realize it. (08 Marks)

- 7 a. The system function of the analog filter is given as  $H_a(s) = \frac{s+0.1}{(s+0.1)^2 + 16}$  obtain the system function of the digital filter using bilinear transformation which is resonant at  $\omega_r = \pi/2$ . (08 Marks)
- b. A Chebyshev filter of order 3 and unit band width has a pole at  $s = -1$ . Find the other two poles. The analog filter is mapped to the z domain using bilinear transformation with  $T = 2$  find  $H(z)$ . (12 Marks)

- 8 a. Compare FIR and IIR. (05 Marks)
- b. A low-pass filter is to be designed with the following desired frequency response

$$H_d(e^{j\omega}) = \begin{cases} e^{-j2\omega} & \frac{\pi}{4} \leq \omega \leq \frac{\pi}{4} \\ 0 & \frac{\pi}{4} \leq |\omega| \leq \pi \end{cases}$$

CMRIT LIBRARY  
BANGALORE - 560 037

determine the filter co-efficients  $h(n)$  if the window function is defined as

$$w(n) = \begin{cases} 1 & 0 \leq n \leq 4 \\ 0 & \text{otherwise} \end{cases}$$

Also determine the frequency response  $H(e^{j\omega})$  of the designed filter.

(15 Marks)

\*\*\*\*\*