



--	--	--	--	--	--	--

Eighth Semester B.E. Degree Examination, Feb./Mar. 2022
Industrial Drives and Applications

Time: 3 hrs.

Max. Marks: 80

Note: Answer any FIVE full questions, choosing ONE full question from each module.

Module-1

- 1 a. With basic block diagram, explain the essential elements of electric Drives. (08 Marks)
- b. Explain the speed torque conventions and multi-quadrant operations. (08 Marks)

OR

- 2 a. Explain the load equalization for fluctuating loads in Electric drives. (08 Marks)
- b. A drive has the following parameters: $J = 10\text{kg-m}^2$, $T = 100 - 0.1N(\text{N-m})$, Passive load Torque $T_\ell = 0.05N(\text{N-m})$ where N is the speed in rpm. Initially the drive is operating in steady state, now it is to be reversed. For this motor characteristics is changed to $T = -100 - 0.1N(\text{n-m})$. Calculate the time of interval. (08 Marks)

Module-2

- 3 a. Mention the different types of classes of motor duty and explain each type in brief. (08 Marks)
- b. Obtain the thermal model of motor for heating and cooling. Also draw the heating and cooling curves. (08 Marks)

OR

- 4 a. Explain with a suitable circuit diagram and waveforms the single semi-controlled converter fed DC separated excited motor drive. (08 Marks)
- b. The speed of a 20HP, 210V, 1000rpm series DC motor is controlled by a 1ϕ full converter. The combined field and armature circuit resistance = 0.25Ω , $K_{af} = 0.03\text{N-m/A}^2$ and $K_{res} = 0.075 \text{ V-S/rad}$. The supply voltage is 230V. Assuming continuous and ripple free motor current, determine the following for firing angle $\alpha = 30^\circ$ and speed $N = 1000\text{rpm}$.
 - i) Motor current
 - ii) Motor Torque
 - iii) Supply power factor. (08 Marks)

Module-3

- 5 a. Derive the expression for maximum torque of a three phase induction motor. (08 Marks)
- b. Explain in detail stator voltage control, also mention its advantages and disadvantages. (08 Marks)

OR

- 6 a. Explain with block diagram static Kramer Drive. (08 Marks)
- b. A 400V, 3ϕ , 50Hz, 6 pole cage induction motor has the following equivalent circuit parameters $R_1 = 0.2\Omega$, $X_1 = 0.5\Omega$, $R_2 = 0.2\Omega$, $X_2 = 0.5\Omega$ and $X_m = 15\Omega$. The motor operates on full load and slip = 0.05. When the two stator terminals are suddenly interchanged, calculate the primary current and the braking torque immediately after application of plugging. (08 Marks)

Important Note : 1. On completing your answers, compulsorily draw diagonal cross lines on the remaining blank pages.
 2. Any revealing of identification, appeal to evaluator and /or equations written eg, 42+8 = 50, will be treated as malpractice.

Module-4

- 7 a. With a neat sketch of waveform and circuit diagram. Explain cyclo converters. (08 Marks)
b. Write short notes on variable frequency control from a current source inverter. (08 Marks)

OR

- 8 a. A 3 ϕ 440V, 6 pole, 50Hz delta connected slip ring induction motor has rotor resistance of 0.3 Ω and leakage reactance of 1 Ω per phase referred to stator. When driving a fan load, it runs at full load at 3% slip. What resistance must be inserted in rotor circuit to obtain a speed of 800rpm? Neglect stator impedance and parameter. The stator to rotor turns ratio is 2.2. (08 Marks)
b. Write a short note on synchronous operation from fixed frequency supply. (08 Marks)

Module-5

- 9 a. Write short notes on:
i) Brushless DC motor drive (04 Marks)
ii) Sinusoidal PM AC motor drive. (04 Marks)
b. With a neat sketch, explain load commutated Thyristor inverter synchronous motor drives. (08 Marks)

CMRIT LIBRARY
BANGALORE - 560 037

OR

- 10 a. Mention in detail the applications of drives in steel rolling mills. (08 Marks)
b. With a neat sketch, explain variable reluctance and permanent magnet stepper motor drive. (08 Marks)

* * * * *