

USN

--	--	--	--	--	--	--	--	--	--

10EC52

Fifth Semester B.E. Degree Examination, July/August 2022
Digital Signal Processing

Time: 3 hrs.

Max. Marks: 100

Note: 1. Answer any FIVE full questions, selecting atleast TWO questions from each Part.
2. Missing data, if any, may be suitably assumed.

PART – A

- 1 a. Derive the relationship of N-point DFT with other transforms. (08 Marks)
- b. Find the N-point DFT of the sequence $x(n) = e^{j\omega n}$ $0 \leq n \leq N-1$ (04 Marks)
- c. Compute 8 point DFT of the sequence $x(n) = (1, 1, 1, 1, 0, 0, 0, 0)$. (08 Marks)
- 2 a. State and prove circulative shift property of DFT. (04 Marks)
- b. Find 4 point DFT of the sequence $x(n) = \cos\left(\frac{\pi}{4}n\right) + \sin\left(\frac{\pi}{4}n\right)$. (08 Marks)
- c. Compute circular convolution of the following sequences :
 $x_1(n) = \{2, 1, 2, 1\}$
 $x_2(n) = \{1, 2, 3, 4\}$. (08 Marks)
- 3 a. Determine number of real multiplications, real additions and trigonometric functions required for direct computation of N-point DFT. (08 Marks)
- b. Find the output $y(n)$ of a filter whose impulse response is $h(n) = \{1, 1, 1\}$ and input signal to the filter is $x(n) = \{1, 2, 0, -3, 4, 2, -1, 1, -2, 3, 2, 1, -3\}$ using overlap add technique. (12 Marks)
- 4 a. Develop Radix-2 DIF FFT algorithm and draw the complete flow graph for an 8 point DFT. (10 Marks)
- b. Compute circular convolution for $N = 4$ using DIT FFT algorithm for the following sequences.
 $x_1(n) = \{2, 1, 1, 2\}$
 $x_2(n) = \{1, -1, -1, 1\}$. (10 Marks)

PART – B

- 5 a. Determine the transfer function $H_a(s)$ of the lowest order Butterworth filter to meet the following specification :
 i) Passband gain $K_p = -1$ db at $\Omega_p = 4$ rad/sec
 ii) Passband attenuation greater than or equal to 20db at $\Omega_s = 8$ rad/sec. (10 Marks)
- b. Let $H(s) = \frac{1}{s^2 + s + 1}$ represent the transfer function of LPF with a passband of 1 rad/sec. by using frequency transformation techniques find the transfer function of the following analog filter.
 i) A high pass filter with a cutoff frequency of 10 rad/sec
 ii) A lowpass filter with a passband of 10rad/sec
 iii) A bandpass filter with a passband of 10rad/sec a centre frequency of 100 rad/sec. (06 Marks)
- c. Mention the important properties of Chebyshev polynomial. (04 Marks)

Important Note : 1. On completing your answers, compulsorily draw diagonal cross lines on the remaining blank pages.
2. Any revealing of identification, appeal to evaluator and /or equations written eg, 42+8 = 50, will be treated as malpractice.

- 6 a. Draw the block diagram of Direct Form-I and Direct Form-II realization for digital IIR filter described by the following system function :

$$H(z) = \frac{8z^3 - 4z^2 + 11z - 2}{(z - \frac{1}{4})(z^2 - z + \frac{1}{2})}. \quad (10 \text{ Marks})$$

- b. Realize the linear phase FIR filter having the following impulse response.

i) $h(n) = \delta(n) + \frac{1}{4}\delta(n-1) - \frac{1}{8}\delta(n-2) + \frac{1}{4}\delta(n-3) + \delta(n-4)$

ii) $h(n) = \delta(n) - \frac{1}{4}\delta(n-1) + \frac{1}{2}\delta(n-2) + \frac{1}{2}\delta(n-3) - \frac{1}{4}\delta(n-4) + \delta(n-5).$ (10 Marks)

- 7 a. Derive an expression for FIR frequency response of Even-N symmetric impulse response. (08 Marks)

- b. An FIR filter is to be designed with the following desired frequency response

$$H_d(e^{j\omega}) = H_d(\omega) = \begin{cases} 0 & -\frac{\pi}{4} < \omega < \frac{\pi}{4} \\ e^{-j2\omega} & \frac{\pi}{4} < |\omega| < \pi \end{cases}$$

Determine the filter co-efficient $h(n)$. If the windows defined by

$$W_R(n) = \begin{cases} 1 & 0 \leq n \leq 4 \\ 0 & \text{otherwise} \end{cases}$$

Also find frequency response of $H(\omega)$. (12 Marks)

- 8 a. Discuss Bilinear transformation method. Also explain the mapping of s-plane to Z plane. (08 Marks)

- b. Convert the analog filter transform function :

$$H_a(S) = \frac{S+1}{S^2 + 5S + 6}$$

CMRIT LIBRARY
BANGALORE - 560 037

into $H(z)$ by using impulse invariant method ($T = 0.1 \text{sec}$). (08 Marks)

- c. Distinguish IIR and FIR filter. (04 Marks)
